

Добрый день.

Обновлять прошивку необходимо через утилиту [BatchConfigTool](#)
Если утилита запускается с ошибкой отсутствия .dll-файлов то
установите [библиотеки](#) Microsoft Visual C++

1. Запустите утилиту от имени Администратора (важно)
2. Выберите онлайн устройство (из нижнего списка) и добавьте в утилиту (верхний список)

Выберите онлайн устр-во
и нажмите +Add (добавить)

Total Number: ...

Refresh

+ Add

Activate

Reset Password

Edit Network Parameters

☐	ID	Device Type	Security	IPv4 Address	Port	Firmware Version	IPv4 Gateway	HTP
☒	001	DS-7616NI-I2/16P	Activated	192.168.88.216	8000	V4.22.005build 191208	192.168.88.1	80

3. Выберите устройство в верхней таблице,нажмите "Upgrade"

Total Number: 1

Refresh

+ Add

× Delete

Upgrade

Batch

Set via ISAPI

Health Monitoring

CGI

UPnP

☒	ID	Device Type	IP Address	Port	Channel	Firmware Version	Serial No
☒	001	DS-7716NI-K4	192.168.88.91	8000	👁	V3.4.112 build 200604	DS-7716

Выберите устройство и нажмите "Upgrade"

4. Нажмите кнопку папки и выберите файл прошивки

Upgrading Mode ☒ File Upgrade ☐ Online Upgrade

File Path



☒ Reboot Device after Upgrading ☐ Delete Device after Upgrading

Configuration

**Нажмите на иконку "папки"
и выберите прикрепленный
файл, формата digicap.dav**

5. После перепрошивки произведите сброс на заводские настройки, нажав в верхней таблице "System Config - Retore"

The screenshot shows a web application window titled 'Configuration'. It features a top toolbar with buttons: Refresh, Add, Delete, Upgrade, Export Upgrade Report, Batch Config, and a search filter. Below the toolbar is a table with columns: Device Type, Device Model, IP Address, Port, Camera, Firmware Version, Custom ID, and Settings. The first row of the table contains the following data: 'Pending Device', 'DS-7616NI-K2/16P', '192.168.88.32', '8000', an eye icon, 'V4.72.107 build 220914', 'Upgrade detec...', and 'DS'. To the right of the table, a 'System Config' dropdown menu is open, showing options: Reboot, Retore (with a red checkmark), Wiper, and Scheduled. The 'Retore' option is highlighted.